

TeCom-Duo

-C

PMR & FreeNET

-H

HAM UHF&VHF

- ◉ Dual-Frequency Display
- ◉ Repeater Shift
- ◉ 5-tone selective calling
- ◉ 50 CTCSS / 105 DCS
- ◉ DTMF

dual
band



English & German
voice annunciation



features

- 128 channels programmable
 - H: 144-148 & 430-440 MHz
 - C: 8 PMR- & 6 FreeNet-channels
- tx power
 - H: max. 4 W/5 W
 - C: 0,5 W
- programmable twin-function key*:
optional signal call, emergency call,
1750 kHz call, monitor
- 5-tone selective call*
(1 decode & 9 encodes)
- 50 CTCSS / 105 DCS codes*
- menu (with 18 functions) -
scan, SQL, TOT, VOX, TX Power, Roger-
Beep, scrambler, beep tone, voice, ANI,
keylock, bandwidth, CTCSS/DCS, etc. *
- selectable display mode*
channel/frequency/name/VFO(only -H)
- transmit blockage on occupied channels*
- transmit- / battery-warning-display*
- transmit-time-out*
- channel scan
- VOX
- SOS function
- FM radio (87-108 MHz)
- timer
- programmable channel name*
- bandwidth*:
 - H: 12.5 kHz, 25 kHz
 - C: 12.5 kHz
- step size : 5K/6.5K/10K/12.5K/
25K/50K/100K* (only -H)
- connection : 2.5/3.5 mm st./st.
- dimensions : 60 x 115 x 34 mm
- weight : 225 g (incl. battery and ant.)
*pc-programmable

versions

TeCom-Duo -H

PR8083

amateur radio - licence required
128 channels programmable
144-146 MHz & 430-440 MHz
max. tx power 4 W / 5 W

TeCom-Duo -C

PR8082

PMR & FreeNet combined in one radio!
no fees - no registration (in Germany only)
8 PMR & 6 FreeNet Kanäle programmed
max. tx power 500 mW

contents

- 1 x TeCom-Duo with SMA-antenna
- 1 x charger with power supply
- 1 x battery pack Li-Poly, 1600 mAh/7.4 V
- 1 x belt clip
- 1 x carrying strap
- 1 x manual