

# CB MOBILE MINICOM

- 🔍 LCD
- 🔍 Scan
- 🔍 priority channel 9/19
- 🔍 Squelch, automatic & manual
- 🔍 Full Multi Norm



### features:

LCD	automatic & manual squelch
RF Gain	priority channel 9 / 19
SCAN	switch AM/FM or UK/EC and scan
frequency norm selection (DE/PL/EC/EI/UK)	DC 12 V
external speaker connection	Up/Down microphone with signal key

dimension : 145 x 30 x 130 mm  
weight : ~ 695 g

**contents :** 1 x CB Mobile MiniCom with fixed microphone, 1 x mounting kit, 1 x power supply cable and manual

### CB Mobile MiniCom Full Multi Norm

CB3208

DE : 80 FM 26.565 - 27.405 MHz / max. 4 W and 40 AM 26.965 - 27.405 MHz / max. 4 W  
 EC : 40 FM 26.965 - 27.405 MHz / max. 4 W  
 EI : 40 FM 26.965 - 27.405 MHz / max. 4 W and 40 AM 26.965 - 27.405 MHz / max. 4 W  
 PL : 40 FM 26.960 - 27.400 MHz / max. 4 W and 40 AM 26.960 - 27.400 MHz / max. 4 W  
 UK : 40 FM 26.60125 - 27.99125 MHz / max. 4 W and 40 FM 26.965 - 27.405 MHz / max. 4 W

approved for : AT, BG, CH, CY, CZ, DE, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LT, LU, LV, MT, NL, PT, PL, RO, SE, SI, SK



### CB Mobile MiniCom hp

CB3209

40 channels FM, 4 W / 40 channels AM, 4 W  
approved in GR, NO, SE